CABLE HISTORICAL OPERATING TEMPERATURE ESTIMATOR

Presented to: North American Transmission & Distribution Conference & Expo June 13-15, 2006, Montreal, Canada

Francisco de León*, Patrick St-Roch, and Christian Beauregard CYME International T&D Inc. 1485 Roberval, Suite 104 St-Bruno (Quebec) - J3V 3P8, Canada Tel. (450) 461 3655 - Fax. (450) 461 0966 info@cyme.com

* Presenter

Keywords: Ampacity; Cable Aging; Cable normal operating temperature; Cable emergency temperature

I. Introduction

There are many underground (UG) transmission/distribution systems in operation for longer than 50 years (a few even longer than 100 years). Utilities are facing the need to provide reliable service with an aging cable infrastructure. UG system planners and operators currently do not know if (which, where, when and for how long) cables have exceeded, at some point in time, their operating or emergency temperature.

There exists a gamut of testing techniques aimed to estimate the age, or more precisely, the remaining life of cables [1-15]. Standardized procedures are listed in references [1-2]. One must distinguish between "thermal aging", "mechanical aging" and "electrical aging". The Cable Historical Operating Temperature Estimator (CHOTE) described in this paper presents a contribution to help determine the thermal age of cables.

CHOTE is a software application offering an innovative way to evaluate the temperature at which underground cable systems have operated during their in-service life. CHOTE is capable of providing answers to the following questions:

- Which cables have exceeded their normal operating temperature and for how long?
- Which cables have exceeded their *emergency temperature* and for how long?
- Given a predicted load growth: when in the future cables will reach their maximum design temperature?

Answers to those questions shall help cable engineers to plan cable additions and substitutions in and informed manner. As a consequence capital investments in cable infrastructure can be managed efficiently.

2. Transient Cable Rating

Cable operating temperature very much depends on the load shape applied to the cable. I other words, the temperature of a cable depends on the intensity of the current and its time variations. Therefore, cables have different ratings, i.e. steady state, cyclic, emergency and short circuit. Since cables installations have thermal inertia, it takes time to heat up the cable and its surroundings.

Transient analyses are typically used to compute cable thermal ratings under emergency situations. However, the same computations can be used in a continuous way to compute the operating temperature of cables in an installation. CHOTE used the transient engine of CYMCAP (CYME International T&D, Cable Ampacity Program) [16] processing historical archived information of cable load shapes.

The inputs for a cable thermal transient simulation are:

- The geometrical distribution and thermal parameters
- Detailed cable construction (including materials)
- Bonding arrangement
- Load shapes for all cables in the installation

The necessary geometrical/thermal parameters depend on the type of installation. For a typical underground installation in North America (cables in duct banks) one would need: duct bank width, height and burial depth; thermal resistivities of the native soil and duct bank; and the soil temperature at burial depth. Figure 1 graphically shows a typical installation.




Figure 1. A typical duct bank installation

The necessary data for a cable includes: cable construction: one core or three core; cable type: extruded, concentric neutral, etc.; the phase-to-phase voltage of the system where the cable will be used; the conductor material and caliber or area; the conductor diameter; the thickness or diameter of every layer of the cable; for example, conductor shield, insulation, insulation screen, sheath, sheath reinforcement, concentric wires, armour bedding, armour, serving, and jacket. Additionally, for some of the layers more information may be needed. For concentric wires even the length of lay and the number of wires is convenient to know. Figure 2 shows the construction details of the two cables used in the sample installation of Figure 1.




Figure 2. Details of cable construction (transmission and distribution)

Loads for transient calculations are typically represented on hourly resolution on duration of 24 to 168 hours. A typical weekly load shape is shown in Figure 3.




Figure 3. Typical weekly load shape in per unit

With the above information transient calculations can be made using the methods described in the standards IEC 287 [17-23] and IEC 853 [24-25]. The underlying principle is to solve an analog thermal-electrical equivalent circuit. Figure 4 depicts a representative circuit. The interested reader can find all the details in the excellent book by Anders, reference [26].




Figure 4. Analog thermal-electrical circuit for the calculation of transients

A typical response to step variation is shown in Figure 5. One can appreciate that the temperature of the cable follows in an exponential way the changes in current.




Figure 5. Typical transient response to a step change

3. Description of CHOTE

Using transient simulations, CHOTE processes archived loading information usually available through the SCADA/PI systems on an hourly (or 15 minutes) resolution. Thus, the input to the temperature estimator is the current of all cables on a particular installation. CHOTE is capable of automatically analyzing all the thermal sections of a system. This may include transmission and even the entire distribution system (manhole-to-manhole). The temperature estimator can process achieved information for any length of time. Currently 10 years of historical data are being used. Figure 6 shows the user interface screen of the application.




Figure 5. CHOTE user interface screen

The output of CHOTE is a list of cable sections that have exceeded the (definable) normal and/or emergency target temperatures. CHOTE produces a global ranking report. The cables that exceed their target (normal/emergency) temperatures for the longest time are given the first place in the report. The output displays not only where, but also when the hot spots have occurred. Figure 6 shows a typical output screen.




Figure 6. Output screen of CHOTE showing the list of cables that exceed the specified normal operating temperature (90°C)

CHOTE is capable of indicating the location of the cables that have exceeded a target, either normal or emergency, temperature. It will give the thermal section (manhole-to-manhole), the feeder name, the dates, times and for how long certain temperature was exceeded (Figure 6). Additionally, the application shows graphically the location of the cable with problems in the duct bank and even allows re-creating the condition that produced the temperature problem (see Figure 7).




Figure 7. The left-hand side shows the location of the cable exceeding the target temperature of 90°C. On the right-hand side is the re-creation of the cable temperature curve. Note how it exceeds the 90°C target

CHOTE can perform what-if scenarios to study the impact of addition of new cables. This facility can also be used to determine the remaining ampacity of one or more of the cables installed in a given duct bank.

4. Technical/Economical Benefits of CHOTE

CHOTE provides important information to transmission and distribution engineers. CHOTE allows identifying, qualifying and quantifying the following important conditions:

- The cables and cable installations that have been exposed to thermal damage. Say which cables have exceeded their *normal and/or emergency temperatures* during their in-service life.
- For how long and for how much the applied over-temperatures compare with the original design characteristics.

Cable engineers can take advantage of the above information to plan additions and/or substitutions in and informed manner. By using CHOTE an engineer knows for how long each cable has exceeded a desired certain target temperature. As a consequence, there is valuable information to estimate the remaining life of a cable, which can be used to manage efficiently capital investments in cable installations. For example, an investment to substitute a cable can be postponed, or planned to do it "just in time", with greater certainty thanks to the information that CHOTE offers.

5. Future Developments of CHOTE

To enhance the analytical power of the cable temperature estimator a load growth analysis facility would be added to allow engineers to determine when in the future a cable will reach its normal and/or emergency temperatures. This will require for CHOTE not only to process available archived historical information, but to look into the future with a given load growth function.

A thermal age model could be introduced in CHOTE. The IEEE standard 1425 [1] proposes the use of the Arrhenius Aging Law. This model has been used extensively, but we believe there is a superior model, based on the rate theory, that does not use empirical knowledge and gives equally reliable results [27-28]. The aging model is an exponential model given by the following expression:

$$t = \frac{h}{kT} e^{\left(\frac{\Delta H - T \Delta S}{kT}\right)}$$

Where:

t = Thermal life (thermal aging) [s]

T = Temperature [°K]

h = Plank constant = 6.62606891x10-34 [J-s]

 $k = \text{Boltzmann constant} = 1.3806505 \times 10-23 \text{ [J/°K]}$

DH = Activation enthalpy (material constant) [kcal/mole] [J]

DS = Activation entropy (material constant) [kcal/(mol-°K)] [J/°K]

DG = DH - TDS = Activation energy [kcal/mole] [J]

6. Conclusions

This paper has introduced the CHOTE (Cable Historical Operating Temperature Estimator) software application. The main purpose of CHOTE is to provide answers on which, where, when and for how long, cables have exceeded their normal operating or emergency temperature. The main idea of CHOTE is to make available a tool to assess the temperature aging of a cable or a cable installation in the context of the entire cable system. As a consequence capital investments in cable installations can be managed efficiently in a timely manner.

6. References

- [1] IEEE Std. 1425-2001 "IEEE guide for the evaluation of the remaining life of impregnated paper-insulated transmission cable systems".
- [2] IEEE Std. 1407-1998 "IEEE trial-use guide for accelerated aging tests for medium-voltage extruded electric power cables using water-filled tanks".

- [3] Abdolall, K.; Halldorson, G.L.; Green, D., "Condition assessment and failure modes of solid dielectric cables in perspective", IEEE Transactions on Power Delivery, Volume 17, Issue 1, Jan. 2002, Page(s): 18–24.
- [4] Sarma, H., "Accelerated life tests on a new water tree retardant insulation for power cables", IEEE Transactions on Power Delivery, Volume 12, Issue 2, April 1997, Page(s): 551 559.
- [5] Walton, M.D.; Bernstein, B.S.; Smith, J.T., III; Thue, W.A.; Groeger, J.H., "Accelerated cable life testing of EPR-insulated medium voltage distribution cables", IEEE Transactions on Power Delivery, Volume 9, Issue 3, July 1994, Page(s): 1195–1208.
- [6] Montanari, G.C., "An investigation on the thermal endurance of EPR model cables", IEEE Transactions on Electrical Insulation, Volume 25, Issue 6, Dec. 1990, Page(s): 1046–1055.
- [7] Rudasill, C.L., Jr.; Ward, D.J., "Distribution underground cable evaluation", IEEE Transactions on Power Delivery, Volume 12, Issue 3, July 1997, Page(s): 1398 1403.
- [8] Srinivas, N.N.; Ahmed, N., "Condition assessment of distribution and transmission class voltage cable systems", 2003 IEEE 10th International Conference Transmission and Distribution Construction, Operation and Live-Line Maintenance, April 6-10, 2003, Page(s): 194–201.
- [9] Singh, N.; Morel, O.E.; Singh, S.K.; Rodenbaugh, T.J., "The assessment of the degree of paper aging and remaining life of fluid-filled paper-insulated high voltage underground transmission cables through wet-tensile strength", Proceedings of the Electrical Electronics Insulation Conference, 1995, and Electrical Manufacturing & Coil Winding Conference, Sept. 18-21, 1995 Page(s): 443–447.
- [10] Mohacsi, G., "On-site examination for predicting the remaining life-time of paper and synthetic insulated cables", 14th International Conference and Exhibition on Electricity Distribution. Part 1. Contributions. (IEE Conf. Publ. No. 438), Volume 3, June 2-5, 1997 Page(s): 10/1 10/5 vol.3.
- [11] Chen Jiqun; Wang Shoutai. "Method of estimating the remaining life of the 10 kV XLPE cable operated 10 years", Proceedings of the 6th International Conference on Properties and Applications of Dielectric Materials, 2000, Volume 1, June 21-26, 2000, Page(s): 204-208.
- [12] Walton, M.D.; Smith, J.T., III; Thue, W.A., "Accelerated aging of extruded dielectric power cables. I. Control and monitoring methodology", IEEE Transactions on Power Delivery, Volume 7, Issue 2, April 1992, Page(s): 596–602.
- [13] Bernstein, B.S.; Thue, W.A.; Walton, M.D.; Smith, J.T., III, "Accelerated aging of extruded dielectric power cables. II. Life testing of 15 kV XLPE-insulated cables", IEEE Transactions on Power Delivery, Volume 7, Issue 2, April 1992, Page(s): 603–608.
- [14] Montanari, G.C.; Cacciari, M., "Progressively-censored aging tests on XLPE-insulated cable models", IEEE Transactions on Electrical Insulation, Volume 23, Issue 3, June 1988, Page(s): 365–372.
- [15] Brown, M., "Accelerated life testing of EPR-insulated underground cable", IEEE Electrical Insulation Magazine, Volume 7, Issue 4, July-Aug. 1991, Page(s): 21–26.
- [16] CYMCAP for Windows, CYME International T&D Inc., December 2005.
- [17] Electric Cables Calculation of the current rating Part 1: Current rating equations (100% load factor) and calculation of losses Section 1: General, IEC Standard 287-1-1 (1994-12).
- [18] Electric Cables Calculation of the current rating Part 1: Current rating equations (100% load factor) and calculation of losses Section 2: Sheath eddy current loss factors for two circuits in flat formation.
- [19] IEC Standard 287-1-2 (1993-11). Electric Cables Calculation of the current rating Part 2: Thermal resistance – Section 1: Calculation of the thermal resistance. IEC Standard 287-2-1 (1994-12).
- [20] Electric Cables Calculation of the current rating Part 2: Thermal resistance Section 2A: A method for calculating reduction factors for groups of cables in free air, protected from solar radiation. IEC Standard 287-2-2 (1995-05).
- [21] Electric Cables Calculation of the current rating Part 3: Sections on operating conditions Section 1: Reference operating conditions and selection of cable type. IEC Standard 287-3-1 (1995-07).
- [22] Calculation of the cyclic and emergency current rating of cables Part 1: Cyclic rating factor for cables up to and including 18/30 (36) kV. IEC Publication 853-1 (1985).
- [23] Calculation of the cyclic and emergency current rating of cables Part 2: Cyclic rating of cables greater than 18/30 (36) kV and emergency ratings for cables of all voltages. IEC Publication 853-2 (1989-07).

- [24] IEC Publication 853-1 (1985), "Calculation of the cyclic and emergency current rating of cables Part 1: Cyclic rating factor for cables up to and including 18/30 (36) kV".
- [25] IEC Publication 853-2 (1989-07), "Calculation of the cyclic and emergency current rating of cables Part 2: Cyclic rating of cables greater than 18/30 (36) kV and emergency ratings for cables of all voltages".
- [26] George Anders, "Rating of Electric Power Cables: Ampacity Computations for Transmission, Distribution, and Industrial Applications", IEEE Press, 1997, ISBN 0-7803-1177-9. It is now available through McGraw-Hill only.
- [27] Dang, C., Parpal, J.L., and Crine J.P., "Electrical Aging of Extruded Dielectric Cables: Review of Existing Theories and Data", IEEE Transaction on Dielectrics and Electrical Insulation, Vol. 3, No. 2, April 1996, pp. 237-247.
- [28] Crine, J.P., "The Compensation Law Revisited: Application to Dielectric Aging", IEEE Transaction on Electrical Insulation, Vol. 26, No. 4, August 1991, pp. 811-818.